

Features

- Highest luminous flux
- Super energy efficiency ٠
- Long Lifetime Operation
- Superior ESD protection
- Superior UV Resistance ٠

Applications

- Read lights (car, bus, aircraft) ٠
- Portable (flashlight, bicycle) •
- Bollards / Security / Garden ٠
- Traffic signaling / Beacons
- In door / Out door Commercial lights ٠
- Automotive Ext


■Absolute Maximum Ratin	(Ta=25℃)		
Item	Symbol	Value	Unit
DC Forward Current	$I_{\rm F}$	400	mA
Pulse Forward Current*	I _{FP}	500	mA
Reverse Voltage	V _R	5	V
Power Dissipation	P _D	1200	mW
Operating Temperature	Topr	-30 ~ +85	°C
Storage Temperature	Tstg	-40~ +100	°C
Lead Soldering Temperature	Tsol	260°C /5sec	-

Anode(+) ቍ Φ Cathode(-) BackView 5 1.51 Anode Cathode -5.06 ழ் ESD Protection Diode 0 $\overline{\mathbf{O}}$ 14 5

•Outline Dimension

Unit:mm Tolerance:±0.30mm

Directivity



/W /W /W RI-A=60 RJ-A=50

60

80

RJ-A=40

B.I-A=30 /W

40

Ambient Temperature, TA (

*Pulse width Max.10ms Duty ratio max 1/10

Electrical -Optical Characteristics

■Electrical -Optical Characteristics			(Ta=25°C)			
Item	Symbol	Condition	Min.	Тур.	Max.	Unit
DC Forward Voltage	$V_{\rm F}$	I _F =350mA	2.0	2.5	3.0	V
DC Reverse Current	I _R	V _R =5V	-	-	10	μA
Domi. Wavelength	λ_{D}	I _F =350mA	620	625	630	nm
Luminous Flux	Φv	I _F =350mA	40	50	-	lm
50% Power Angle	2 0 1/2	I _F =350mA	-	140	-	deg

Note: Don't drive at rated current more than 5s without heat sink for Xeon 1 emitter series.

LED & Application Technologies







20



100

400 350

300 250 200

150

100

50 0 0

Forward Current, IF (mA)

■Forward Operating Current (DC)



Xeon 1 Power Red LED

OSR5XME1E1E

VER C.0

Handling of Silicone Lens LEDs

Notes for handling of silicone lens LEDs

- Please do not use a force of over 3kgf impact or pressure on the silicone lens, otherwise it will cause a catastrophic failure.
- The LEDs should only be picked up by making contact with the sides of the LED body.
- Avoid touching the silicone lens especially by sharp tools such as Tweezers.
- Avoid leaving fingerprints on the silicone lens.
- Please store the LEDs away from dusty areas or seal the product against dust.
- When populating boards in SMT production, there are basically no restrictions regarding the form of the pick and place nozzle, except that mechanical pressure on the silicone lens must be prevented.
- Please do not mold over the silicone lens with another resin. (epoxy, urethane, etc)

